

200 tdi glow plug relay wiring.



1. Brown to battery+ feed
2. Thick yellow/black tracer to number 4 glow plug
3. White/red tracer to Igniton switch
4. White to any white in vechile harness
5. Thin yellow/black tracer to warning(choke) on dash
6. Black to earth ÷



- 1) Live feed from Starter / alternator connection or possibly original glow plugswitch.[Brown]

30

- 2) Feed to glow plugs [yellow / black disco] 87
- 3) Timer start signal???? [white / red disco starter solenoid signal] 50
- 4) White is ignition on live starts the relay.86
- 5) Dash glow plug light [Black] this earths the choke lamp when relay energised.L
- 6) Earth [Disco black / yellow] 85